




Techstep Essentials MDM

Work profile restrictions


Date: 16/03/2023



To edit the Work profile restrictions policy settings, click Policies -> Change Settings



Choose the Work profile restrictions policy category



Within Work profile restrictions policy there are several settings that you can add to your policies.

Policy settings management ×

Select settings section Set value Select policies Summary

Search

Work profile restrictions

- ☐ Block screen capture Fully managed BYOD/WPC Shared device
- ☐ **Disable accounts modification** Fully managed BYOD/WPC Shared device
- ☐ Block creation of the mail account (Disable accounts modification) Fully managed BYOD/WPC Shared device
- ☐ Block creation of LDAP account (Disable accounts modification) Fully managed BYOD/WPC
- ☐ Block creation of Samsung account (Disable accounts modification) Fully managed BYOD/WPC
- ☐ Accounts creation using Google Play Fully managed
- ☐ Disable camera Fully managed BYOD/WPC Shared device
- ☐ Disable cross profile copy-paste Fully managed BYOD/WPC
- ☐ **Disable application control** Fully managed BYOD/WPC Shared device
 The following user actions will be denied when this restriction is enabled: apps uninstalling, disabling apps, clearing app caches, clearing app data, force stopping apps and clearing app defaults.
- ☐ **Disable one lock code** Fully managed BYOD/WPC
 In order to disable active one lock code, Settings for work profile lock code configuration should be applied before.

[Back](#) [Next](#)

Choose the setting you want to configure and click next.

Below is a table of all the settings you can configure within this category with an explanation. In fully managed policy options are available only when policy has work profile defined (old COPE setup).

Parameter	Value	Compatibility
General Settings		
Enable unknown sources	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Block screen capture	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Disable accounts modification	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Block creation of the mail account (Disable account modification)	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Block creation of LDAP account (Disable account modification)	Possible options: <input type="radio"/> Yes or no	Fully Managed BYOD/WPC

	Default value: No	
Block creation of Samsung account (Disable account modification)	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Accounts creation using Google Play	Possible options: <input type="radio"/> Enabled or disabled Default value: Enabled	Fully Managed
Disable camera	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Disable cross profile copy-paste	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Disable application control	Possible options: <input type="radio"/> Yes or no Default value: No (The following user actions will be denied when this restriction is enabled: apps uninstalling, disabling apps, clearing app caches, clearing app data, force stopping apps and clearing app defaults).	Fully Managed BYOD/WPC
Disable one lock code	Possible options: <input type="radio"/> Yes or no Default value: No (In order to disable active one lock code, Settings for work profile lock code configuration should be applied before).	Fully Managed BYOD/WPC
Allow moving apps to work profile	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Block NFC	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Disallow outgoing beam using NFC (Block NFC)	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Allow moving files from device to work profile	Possible options: <input type="radio"/> Yes or no	Fully Managed BYOD/WPC

	Default value: No	
Allow moving files from work profile to device	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Block change of the sharing of the calendar to the personal mode	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Block change of the sharing of the calendar to work profile	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Enable Bluetooth	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Enable file sharing via Bluetooth in work profile (Enable Bluetooth)	Possible options: <input type="radio"/> Yes or no Default value: No	BYOD/WPC
Block Share Via List	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Prevent users from configuring credentials in the managed keystore	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Maximum time the work profile is allowed to be turned off	Possible options: <input type="radio"/> Disabled <input type="radio"/> 3, 4, 5 or 6 days Default value: Disabled (The minimum value is 3 days)	Fully Managed BYOD/WPC
Enable the ability to restore of the backup from the Google account	Possible options: <input type="radio"/> Yes or no Default value: No	Fully Managed BYOD/WPC
Disable location config	Possible options: <input type="radio"/> Yes or no Default value: No	BYOD/WPC
Disable location sharing	Possible options: <input type="radio"/> Yes or no Default value: No	BYOD/WPC
Disable content capture	Possible options: <input type="radio"/> Yes or no Default value: No	BYOD/WPC
Disable content suggestions	Possible options: <input type="radio"/> Yes or no	BYOD/WPC

	Default value: No	
--	-------------------	--

Configure the setting to the wanted value and click next.

Policy settings management ×

Progress: Select settings section (●) — Set value (○) — Select policies (●) — Summary (●)

Work profile restrictions

Block screen capture:

☐ No

[Back](#) [Next](#)

Select the policies you want to add the setting to (You can choose multiple policies) and click next.

Policy settings management ×

Progress: Select settings section (●) — Set value (●) — Select policies (○) — Summary (●)

Block screen capture: No

2 1 – 3 of 3 |< < > >|

	Policy name	Policy mode	Affected devices count	Is default	User Groups	Device groups
<input checked="" type="checkbox"/>	Default BYOD/WPC policy	BYOD/WPC	3	Yes		
<input type="checkbox"/>	Default shared device policy	Shared device	0	Yes		
<input checked="" type="checkbox"/>	Test WPC Ricardp	BYOD/WPC	0	No	Test WPC Ricardo	

[Back](#) [Next](#)

You will then be showed a summary of your applied settings and if there are devices affected by the change.

Click Apply to set your configuration change into effect.

Note: When pressing apply, the settings will be applied on the affected devices immediately.

Policy settings management

×

Select settings section

Set value

Select policies

Summary

Summary:

Number of selected policies: 2

Number of affected devices: 3

Settings:

Block screen capture: No

⚠ Changes in the selected policies will affect some devices. Make sure it's intended.

Back

Apply